

Soundsphere

10 Research Dr Stratford CT 06615

For technical support call 203-386-9200

Soundsphere® Model TX-30 (25V, 70.7V, 100V Constant Voltage) Transformer Installation Instructions

The Soundsphere® Model TX-30 is designed for use with the Model 110B or Model Q-6 loudspeakers. Power taps are provided for 100V, 70V, and 25V systems:

	25V	70V	100V
White	30 Watts	----	----
Orange	15 Watts	----	----
Yellow	7.5 Watts	----	----
Brown	3.8 Watts	30 Watts	----
Blue	1.9 Watt	15 Watts	30 Watts
Violet	0.9 Watts	7.5 Watts	15 Watts
Green	0.5 Watts	3.8 Watts	7.5 Watts
Black	Common	Common	Common

Remember to clip and insulate unused input wires; shorting any input wire to another will reduce the volume level and place an unexpected load on the power amplifier.

When ordered with the Model 110B or Model Q-6, the TX-30 is mounted to the back of the reflector and the loudspeaker driver connections are made at the factory.

Use either black wire for input common or driver (-) connection.

